500 mA, 30 V Schottky Barrier Diode

These Schottky barrier diodes are optimized for low forward voltage drop and low leakage current that offers the most optimal power dissipation in applications. They are housed in spacing saving micro-packaging ideal for space constraint applications.

Features

- Low Forward Voltage Drop 370 mV (Typ.) @ $I_F = 500 \text{ mA}$
- Low Reverse Current 52 μ A (Typ.) @ $V_R = 30 \text{ V}$
- 500 mA of Continuous Forward Current
- High Switching Speed
- These Devices are Pb-Free, Halogen Free/BFR Free and are RoHS Compliant

Typical Applications

- LCD and Keypad Backlighting
- Camera Photo Flash
- Buck and Boost dc-dc Converters
- Reverse Voltage and Current Protection
- Clamping & Protection

MAXIMUM RATINGS

| Rating | Symbol | Value | Unit |
|---|------------------|-------|------|
| Reverse Voltage | V_{R} | 30 | V |
| Forward Current (DC) | | 500 | mA |
| Forward Surge Current (60 Hz @ 1 cycle) | (_{FSM} | 3.0 | Α |
| Repetitive Peak Forward Current (Pulse Wave = 1 sec, Duty Cycle = 66%) | 1 _{FRM} | 1.5 | Α |


Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

1



ON Semiconductor®

www.onsemi.com





ORDERING INFORMATION

| Device | Package | Shipping† | | |
|----------------|----------------------|-----------|--|--|
| NSR05T30XV2T5G | SOD-523 (Pb-Free) | | | |

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

THERMAL CHARACTERISTICS

| Characteristic | Symbol | Min | Тур | Max | Unit |
|---|------------------------------------|-------------|-----|------------|------------|
| Thermal Resistance Junction-to-Ambient (Note 1) Total Power Dissipation @ T _A = 25°C | R _{θJA} P _D | | | 489 250 | °C/W mW |
| Thermal Resistance Junction-to-Ambient (Note 2) Total Power Dissipation @ T _A = 25°C | R _{θJA} P _D | | | 358 350 | °C/W mW |
| Junction and Storage Temperature Range | T _J , T _{stg} | -55 to +150 | | °C | |

- 1. Mounted onto a 4 in square FR-4 board 50 mm sq. 1 oz. Cu 0.06" thick single sided. Operating to steady state.
- 2. Mounted onto a 4 in square FR-4 board 650 mm sq. 1 oz. Cu 0.06" thick single sided. Operating to steady state.




Figure 1. Thermal Response (Note 1)





Figure 2. Thermal Response (Note 2)

ELECTRICAL CHARACTERISTICS ($T_A = 25^{\circ}C$ unless otherwise noted)

| , | | | | | |
|--|-----------------|-----|--------------------------|--------------------------|------|
| Characteristic | Symbol | Min | Тур | Max | Unit |
| Reverse Leakage (V _R = 10 V) (V _R = 30 V) | I _R | | 30 52 | 110 170 | μΑ |
| Forward Voltage $(I_F = 10 \text{ mA})$ $(I_F = 100 \text{ mA})$ $(I_F = 200 \text{ mA})$ $(I_F = 500 \text{ mA})$ | V _F | | 200 275 205 370 | 340 380 420 450 | mV |
| Total Capacitance (V _R = 1.0 V, f = 1.0 MHz) | C _T | | 85 | | pF |
| Reverse Recovery Time (I _F = I _R = 10 mA, I _{R(REC)} = 1.0 mA, Figure 3) | t _{rr} | | 23 | | ns |
| Peak Forward Recovery Voltage (I _F = 100 mA, t _r = 20 ns, Figure 4) | V_{FRM} | | 395 | | mV |



Notes: 1. A 2.0 k Ω variable resistor adjusted for a Forward Current (I_F) of 10 mA. 2. Input pulse is adjusted so I_{R(peak)} is equal to 10 mA.

3. t_n » t_n

Figure 3. Recovery Time Equivalent Test Circuit





Figure 4. Peak Forward Recovery Voltage Definition

TYPICAL CHARACTERISTICS





SOD-523 1.20x0.80x0.60 CASE 502 **ISSUE F**


DATE 08 FEB 2024

NOTES:

- DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 2018. 1.
- CONTROLLING DIMENSION: MILLIMETERS.

 MAXIMUM LEAD THICKNESS INCLUDES LEAD FINISH,
 MINIMUM LEAD THICKNESS IS THE MINIMUM THICKNESS OF BASE MATERIAL.
- DIMENSIONS D AND E DO NOT INCLUDE MOLD FLASH, PROTRUSIONS, OR GATE BURRS.

| | MILLIMETERS | | | |
|-----|-------------|------|------|--|
| DIM | MIN. | N□M. | MAX. | |
| А | 0.50 | 0.60 | 0.70 | |
| b | 0.25 | 0.30 | 0.35 | |
| C | 0.07 | 0.14 | 0.20 | |
| D | 1.10 | 1.20 | 1.30 | |
| Е | 0.70 | 0.80 | 0.90 | |
| Н | 1.50 | 1.60 | 1.70 | |
| L | 0.30 REF | | | |
| L2 | 0.15 | 0.20 | 0.25 | |





RECOMMENDED MOUNTING FOOTPRINT

*For additional information on our Pb-Free strategy and soldering details, please download the DN Semiconductor Soldering and Mounting Techniques Reference manual SOLDERRM/D.


Α В 0.08(M)AB







GENERIC MARKING DIAGRAM*



XX = Specific Device Code М Date Code

*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "■", may or may not be present. Some products may not follow the Generic Marking.

PIN 1. CATHODE (POLARITY BAND)

NO POLARITY

SOD-523 1.20x0.80x0.60

Electronic versions are uncontrolled except when accessed directly from the Document Repository. **DOCUMENT NUMBER:** 98AON11524D Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.

PAGE 1 OF 1

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

DESCRIPTION:

onsemi, Onsemi, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. Onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales