

NCP1680

Totem-Pole Critical Conduction Mode (CrM) Power Factor Correction Controller

Product Overview

For complete documentation, see the data sheet.

The NCP1680 is a CrM PFC controller IC designed to drive the bridgeless totem-pole PFC topology. The bridgeless totem-pole PFC is a power factor correction architecture that consists of a fast switching leg driven at the PWM switching frequency and a second leg that operates at the AC line frequency. This topology eliminates the diode bridge present at the input of a conventional PFC circuit, allowing significant improvement in the power stage efficiency.

Features

- Totem Pole PFC Topology Eliminates Input Diode Bridge
- Critical Conduction Mode (CrM) Operation
- Discontinuous Conduction Mode (DCM) with Valley Turn On Under Light Load Condition
- Frequency Foldback in DCM With 25 kHz Minimum Frequency
- Skip Mode in Very Light Load Condition
- Proprietary Current Sense Scheme
- Digital Voltage Loop Compensation
- AC Line Monitoring Circuit & AC Phase Detection
- Near Unity Power Factor in All Operating Modes
- PFC OK Indicator
 For more features, see the data sheet

Applications

- Power Factor Correction
- Offline Power Supply

End Products

- Industrial Power Supplies
- Telecom 5G Power
- Networking Power
- Gaming Console Power Supplies
- UHD TV Power Supplies

Part Electrical Specifications																			
Product	Status	Compilance	PF C Mo de	Fre qu en cy Op era tio n	Co ntr ol Mo de	To pol og y	f _{SW} Ty p (kH z)	V _{CC} Ma x (V)	Dri ve Ca p. (m A)	UV LO (V)	Lat ch	UV P	Inh ibit ion	Pa cka ge Ty pe	Ca se Ou tlin e	MS L Ty pe	MS L Te mp (°C	Co nta ine r Ty pe	Co nta ine r Qt y.
NCP1680AAD1R 2G	Active	1 30	CR M	Var iabl e	Cu rre nt/ Vol tag e Mo de	Tot em Pol e	Var iabl e	30	10 0 / 10 0	10. 5	Ye s	Ye s	No	SOI C- 16	751 B- 05. PD F	1	26 0	RE EL	25 00
NCP1680ABD1R 2G	Active	@ ②	CR M	Var iabl e	Cu rre nt/ Vol tag e Mo de	Tot em Pol e	Var iabl e	30	10 0 / 10 0	10. 5	Ye s	Ye s	No	SOI C- 16	751 B- 05. PD F	1	26 0	RE EL	25 00
NCP1680ACD1R 2G	Active	19 @	CR M	Var iabl e	Cu rre nt/ Vol tag e Mo de	Tot em Pol e	Var iabl e	30	10 0 / 10 0	10. 5	Ye s	Ye s	No	SOI C- 16	751 B- 05. PD F	1	26 0	RE EL	25 00