Onsemi

ESD and Surge Protection Device, Bidirectional, 15 V

Micro-Packaged Diodes for ESD Protection

ESDL4151

The ESDL4151 is designed to protect voltage sensitive components that require low capacitance from ESD and transient voltage events. Excellent clamping capability, low capacitance, low leakage, and fast response time, make these parts ideal for ESD protection on designs where board space is at a premium. Because of its low capacitance, the part is well suited for use in high frequency designs such as USB 2.0/3.0 high speed applications.

Features

- Low Capacitance 0.8 pF (Typ)
- Low Clamping Voltage
- Small Body Outline Dimensions: 1.00 mm x 0.60 mm
- Low Body Height: 0.23 mm
- Stand-off Voltage: 15 V
- Protection for the following IEC Standards: IEC61000-4-2 Level 4: ±30 kV Contact Discharge IEC61000-4-5 (Lightning): 53 V Input (8/20 μs)
- are ROHS • These Devices are Pb-Free, Halogen Free/BFR Free and are RoHS Compliant

Typical Applications


- USB 2.0/3.0
- MHL 2.0
- eSATA

MAXIMUM RATINGS

Rating	Symbol	Value	Unit
IEC 61000-4-2 (ESD) Contact Air	Ĺ	±30 ±30	kV
Junction and Storage Temperature Range	T _J , T _{stg}	–55 to +150	°C
Lead Solder Temperature – Maximum (10 Second Duration)	ΤL	260	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

See Application Note AND8308/D for further description of survivability specs.



ORDERING INFORMATION


Device	Package	Shipping [†]
ESDL4151MX4T5G	X3DFN2	8000 / Tape &
R I	(Pb-Free)	Reel

For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

ELECTRICAL CHARACTERISTICS

(T_A = 25°C unless otherwise noted)

· · ·	,
Symbol	Parameter
I _{PP}	Maximum Reverse Peak Pulse Current
V _C	Clamping Voltage @ I _{PP}
V _{RWM}	Working Peak Reverse Voltage
I _R	Maximum Reverse Leakage Current @ V _{RWM}
V _{BR}	Breakdown Voltage @ I _T
Ι _Τ	Test Current



*See Application Note AND8308/D for detailed explanations of datasheet parameters.


Parameter	Symbol	Conditions	Min	Тур	Max	Unit
Reverse Working Voltage	V _{RWM}	I/O Pin to GND			45	V
Breakdown Voltage	V _{BR}	I _T = 1 mA, I/O Pin to GND	15.5	16.6	19.5	V
Reverse Leakage Current	I _R	@ 3.3 V, I/O Pin to GND @ 15 V, I/O Pin to GND	, E	Nv	0.1 1.0	μA
Clamping Voltage	V _C	Per IEC61000-4-2, ±8 kV Contact	See	e Figures 1 &	<u>k</u> 2	V
Clamping Voltage TLP (Note 1)	V _C	I _{PP} = 8 A IEC61000–4–2 Level 2 Equivalent (±4 kV Contact, ±8 kV Air)	sem	21,3		V
		IPP = 16 A IEC61000-4-2 Level 4 Equivalent (±8 kV Contact, ±16 kV Air)	2MA	22.9		V
Reverse Peak Pulse Current	I _{PP}	IEC61000-4-5 (8x20 μs) Input Voltage	53			V
		IEC61000-4-5 (8x20 µs) per Figure 11	11			А
Clamping Voltage 8x20 µs Waveform per Figure A (Note 2)	Vc	IEC61000-4-5 (8x20 μs) Input Voltage = 53 V		23	26	V
Dynamic Resistance	R _{DYN}	I/O Pin to GND (8x20 μs)		0.43		Ω
Junction Capacitance	G)	V _R = 0 V, f = 1 MHz		0.80	1.0	pF

FLECTRICAL CHARACTERISTICS (T. 25°C unless otherwise specified)

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.
1. ANSI/ESD STM5.5.1 - Electrostatic Discharge Sensitivity Testing using Transmission Line Pulse (TLP) Model. TLP conditions: Z0 = 50, tp = 100 ns, tr = 1 ns, averaging window; t1 = 70 ns to t2 = 90 ns.
2. Non-repetitive current pulse at T_A = 25°C, per IEC61000-4-5 waveform.


ESDL4151

TYPICAL CHARACTERISTICS



ESDL4151

TYPICAL CHARACTERISTICS



IEC 61000-4-2 Spec.

Level	Test Volt- age (kV)	First Peak Current (A)	Current at 30 ns (A)	Current at 60 ns (A)
1	2	7.5	4	2
2	4	15	8	4
3	6	22.5	12	6
4	8	30	16	8






Figure 10. IEC61000-4-2 Spec



ESD Voltage Clamping

For sensitive circuit elements it is important to limit the voltage that an IC will be exposed to during an ESD event to as low a voltage as possible. The ESD clamping voltage is the voltage drop across the ESD protection diode during an ESD event per the IEC61000-4-2 waveform. Since the IEC61000-4-2 was written as a pass/fail spec for larger systems such as cell phones or laptop computers it is not


clearly defined in the spec how to specify a clamping voltage at the device level. ON Semiconductor has developed a way to examine the entire voltage waveform across the ESD protection diode over the time domain of an ESD pulse in the form of an oscilloscope screenshot, which can be found on the datasheets for all ESD protection diodes. For more information on how **onsemi** creates these screenshots and how to interpret them please refer to AND8307/D.





X3DFN2 1.0x0.6, 0.65P CASE 514AG ISSUE O


DATE 05 DEC 2018



NOTES:

- 1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 2009.
- 2. CONTROLLING DIMENSION: MILLIMETERS

	MILLIMETERS		
DIM	MIN.	NOM.	MAX.
А	0.20	0.23	0.26
A1	0.00		0.03
b	0.45	0.50	0.55
D	0.95	1.00	1.05
E	0.55	0.60	0.65
е	0.65 BSC		
L	0.20	0.25	0.30
L2	0.10 REF		



RECOMMENDED MOUNTING FOOTPRINT

For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "•", may or may not be present. Some products may not follow the Generic Marking.

XX = Specific Device Code = Date Code Μ

0

GENERIC **MARKING DIAGRAM***

XX M

BOTTOM VIEW

Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. **DOCUMENT NUMBER:** 98AON01136H X3DFN2 1.0x0.6, 0.65P **DESCRIPTION:** PAGE 1 OF 1

2X L

onsemi and OnSemi are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make charges without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products herein. special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

© Semiconductor Components Industries, LLC, 2018

L2-

onsemi, ONSEMI, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent_Marking.pdf</u>. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or indental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification. Buyer shall indemnify and hold onsemi and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs,

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

Technical Library: www.onsemi.com/design/resources/technical-documentation onsemi Website: www.onsemi.com

ONLINE SUPPORT: <u>www.onsemi.com/support</u> For additional information, please contact your local Sales Representative at <u>www.onsemi.com/support/sales</u>